



Passionate about protection and control

THREE PHASE RELAYS

NFC

PHASE/
NEUTRAL LOSS

PHASE REVERSAL

PHASE ASYMMETRY

UNDER VOLTAGE

OVER VOLTAGE

TIME DELAY

UL LISTED



THREE PHASE RELAYS

LPMRN/2

Programmable using Smartphone with NFC



NEW

Benefits:

- ✓ User profiles for quick/convenient setting up using app
- ✓ Real time monitoring of supply
- ✓ Compact size (only 17.5mm wide)
- ✓ Clone settings on further units
- ✓ Accuracy - 100% digital setting
- ✓ Tamperproof
- ✓ Program without power applied

Key Features:

- Programmable functions for total flexibility
- Customisable
- Monitors own supply (3 and 4-wire)
- Configurable trip and time settings
- Multi-voltage supply options
- 2 x SPDT independent relays outputs assignable to various functions
- Intelligent LED indication



GET IT ON Google Play

Dims: to DIN 43880
W. 17.5mm

LPRC/2

Under & Over Voltage, Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Selectable nominal voltages to suit most popular 3-wire/4-wire supply voltages
- Monitors own supply and measures phase to phase (3-wire monitoring) or phase to neutral (4-wire monitoring) voltages
- Detects if one or more phases exceed the set Under or Over voltage trip levels
- Detects incorrect phase sequence, phase and neutral loss¹
- Independent relay outputs - Under voltage and Over voltage monitoring
- 2 x SPDT relay output - 5A
- Green LED indication for supply status and individual Red LED indication for both relay statuses

¹ when 4-wire mode selected



Dims: to DIN 43880
W. 17.5mm

LPRT/2

Under Voltage, Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Selectable nominal voltages to suit most popular 3-wire/4-wire supply voltages
- Monitors own supply and measures phase to phase (3-wire monitoring) or phase to neutral (4-wire monitoring) voltages
- Detects an Under voltage condition on one or more phases
- Detects incorrect phase sequence, phase and neutral loss¹
- DPDT relay output - 5A
- Green LED indication for supply status
- Red LED indication for relay status

¹ when 4-wire mode selected



Dims: to DIN 43880
W. 17.5mm

LPRD/2

Under Voltage, Phase Loss, Sequence + Restart Delay

Key Features:

- True R.M.S. monitoring
- Selectable nominal voltages to suit most popular 3-wire/4-wire supply voltages
- Monitors own supply and measures phase to phase (3-wire monitoring) or phase to neutral (4-wire monitoring) voltages
- Detects an Under voltage condition on one or more phases
- Detects incorrect phase sequence, phase and neutral loss¹
- Delay to relay re-energising adjustable
- DPDT relay output - 5A
- Green LED indication for supply status and Red LED indication for relay status

¹ when 4-wire mode selected



Dims: to DIN 43880
W. 17.5mm

LPMP/2 & LPRA/2

Phase Asymmetry, Under & Over Voltage, Phase Loss + Restart Delay

Key Features:

- True R.M.S. monitoring
- Selectable nominal voltages to suit popular 3-wire/4-wire supply voltages
- Monitors own supply
- Detects phase asymmetry/unbalance and if one or more phases exceed the fixed Under or Over voltage trip levels (LPRA/2 Under voltage trip level only)
- Detects incorrect phase sequence, phase and neutral loss¹
- Delay to relay re-energising adjustable (LPMP/2 only)
- DPDT relay output - 5A
- Green LED indication for supply status and Red LED for relay status



Dims: to DIN 43880
W. 17.5mm

PUVR44

Phase Under Voltage (High Immunity)

Key Features:

- Designed to withstand voltage overloads up to **125% (cont.)**, **150% (10s)**
- Selectable nominal voltages (**220, 230, 240, 254, 265, 277V (L>N)**)
- Monitors own supply and measures phase to neutral voltages
- Detects an Under voltage condition on one or more phases
- Adjustable Differential and Under voltage trip level
- Adjustable time delay
- DPDT relay output - 8A
- Green LED indication for supply status
- Red LED indication for relay status



Dims: to DIN 43880
W. 44mm

LXPRC/S & LXPRC/S-4W

Under & Over Voltage, Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Can be specified for **110, 208, 220, 380, 400 or 415V** supplies
- Monitors own supply and measures phase to phase voltages (phase to neutral on LXPRC/S-4W)
- Detects if one or more phases exceed the set Under or Over voltage trip levels
- Detects incorrect phase sequence and phase loss (plus neutral loss on LXPRC/S-4W)
- Adjustable Under and Over voltage trip levels
- Adjustable time delay to prevent nuisance tripping
- 1 x SPDT relay output - 8A
- Green LED indication for supply and Red LED for relay status



Dims: to DIN 43880
W. 17.5mm

LXPRC & LXPRC-4W


Under & Over Voltage + Phase Loss

Key Features:

- True R.M.S. monitoring
- Can be specified for **110, 208, 220, 380, 400 or 415V** supplies
- Monitors own supply and measures phase to phase voltages (phase to neutral on LXPRC-4W)
- Detects if one or more phases exceed the set Under or Over voltage trip levels
- Detects phase loss (and neutral loss on LXPRC-4W) and operates irrespective of phase sequence
- Adjustable Under and Over voltage trip levels
- Adjustable time delay to prevent nuisance tripping
- 1 x SPDT relay output - 8A
- Green LED indication for supply and Red LED for relay status



Dims: to DIN 43880
W. 17.5mm



LXPRT & LXPRT-4W

Under Voltage, Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Suits key global supply voltages
- Monitors own supply and measures phase to phase voltages (phase to neutral on LXPRT-4W)
- Detects an Under voltage condition on one or more phases
- Detects incorrect phase sequence and phase loss (plus neutral loss on LXPRT-4W)
- Adjustable Under voltage trip level
- Adjustable time delay to prevent nuisance tripping
- 1 x SPDT relay output - 8A
- Green LED indication for supply status
- Red LED indication for relay status



*Dims:
to DIN 43880
W. 17.5mm*



LXPRF & LXPRF-4W

Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Suits key global supply voltages
- Monitors own supply and measures phase to phase voltages (phase to neutral on LXPRF-4W)
- Detects an Under voltage condition on one or more phases
- Detects incorrect phase sequence and phase loss (plus neutral loss on LXPRF-4W)
- Fixed Under voltage trip level
- Fixed time delay
- 1 x SPDT relay output - 8A
- Green LED indication for supply status
- Red LED indication for relay status



*Dims:
to DIN 43880
W. 17.5mm*



LXPRC/S/RD

Under & Over Voltage, Loss, Sequence + Restart Delay

Key Features:

- True R.M.S. monitoring
- Selectable nominal voltages
- Two ranges available:
 - 208/220V
 - 380/400/415/440/460V
- Monitors own supply and measures phase to phase voltages
- Detects if one or more phases exceed the fixed Under or Over voltage trip levels
- Detects incorrect phase sequence and loss
- Fixed Under/Over voltage trip levels (+/-10% of selected nominal)
- Adjustable Restart time delay (1 - 500s)
- 1 x SPDT relay output - 8A
- Green LED indication for supply status
- Red LED indication for relay status



*Dims:
to DIN 43880
W. 17.5mm*



LXPRC/S/F

Under & Over Voltage, Phase Loss + Sequence

Key Features:

- True R.M.S. monitoring
- Designed primarily for 400/415V supplies
- Monitors own supply and measures phase to phase voltages
- Detects if one or more phases exceed the fixed Under or Over voltage trip levels
- Detects incorrect phase sequence and phase loss
- Fixed Under/Over voltage trip levels
- Adjustable time delay to prevent nuisance tripping
- 1 x SPDT relay output - 8A
- Green LED indication for supply status/fault condition
- Red LED indication for relay status



*Dims:
to DIN 43880
W. 17.5mm*



NOTE: Many other versions and options available which can be customised to suit your requirements!



Broyce Control Ltd. Pool Street, Wolverhampton,
West Midlands, WV2 4HN. U.K.
Tel: +44 (0) 1902 773746 Fax: +44 (0) 1902 420639
Email: sales@broycecontrol.com Web: www.broycecontrol.com



ISO 9001:2015
Cert. No. 14125771